

AD-A160 325 ANALYSIS OF PREPROCESSORS AND DECISION AIDS IN  
ORGANIZATIONS(U) MASSACHUSETTS INST OF TECH CAMBRIDGE  
LAB FOR INFORMATION AND D. G H CHYEN ET AL. FEB 85  
UNCLASSIFIED LIDS-P-1438 AFOSR-TR-85-0019 AFOSR-80-0229 F/G 5/1


1/1

NL

END

FILMED

DTIC



MICROCOPY RESOLUTION TEST CHART  
NATIONAL BUREAU OF STANDARDS-1963-A

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE

## REPORT DOCUMENTATION PAGE

1a. REPORT SECURITY CLASSIFICATION UNCLASSIFIED			1b. RESTRICTIVE MARKINGS		
1c. SECURITY CLASSIFICATION AUTHORITY			3. DISTRIBUTION/AVAILABILITY OF REPORT Approved for public release; distribution unlimited.		
1d. DECLASSIFICATION/DOWNGRADING SCHEDULE			5. MONITORING ORGANIZATION REPORT NUMBER(S) <b>AFOSR-TR- 85-0819</b>		
PERFORMING ORGANIZATION REPORT NUMBER(S) LIDS-P-1438			7a. NAME OF MONITORING ORGANIZATION Air Force Office of Scientific Research		
NAME OF PERFORMING ORGANIZATION Massachusetts Institute of Technology		8d. OFFICE SYMBOL (If applicable)	7b. ADDRESS (City, State and ZIP Code) Directorate of Mathematical & Information Sciences, Bolling AFB DC 20332-6448		
ADDRESS (City, State and ZIP Code) Laboratory for Information and Decision Systems, Cambridge MA 02139		9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER AFOSR-80-0229			
NAME OF FUNDING/SPONSORING ORGANIZATION AFOSR		8b. OFFICE SYMBOL (If applicable) NM	10. SOURCE OF FUNDING NOS.		
8c. ADDRESS (City, State and ZIP Code) Bolling AFB DC 20332-6448		PROGRAM ELEMENT NO. 61102F	PROJECT NO. 2304	TASK NO. A1	WORK UNIT NO.
11. TITLE (Include Security Classification) ANALYSIS OF PREPROCESSORS AND DECISION AIDS IN ORGANIZATIONS					
12. PERSONAL AUTHOR(S) Gloria H.-L. Chyen, Alexander H. Levis					
13a. TYPE OF REPORT Technical		13b. TIME COVERED FROM _____ TO _____		14. DATE OF REPORT (Yr., Mo., Day) FEB 85	
15. PAGE COUNT 7					
16. SUPPLEMENTARY NOTATION					
17. COSATI CODES			18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)		
FIELD	GROUP	SUB. GR.			
19. ABSTRACT (Continue on reverse if necessary and identify by block number) The use of preprocessors and decision aids in command, control and communication (C <sup>3</sup> ) systems is meant to reduce the workload of individual decisionmakers and improve the quality of an organization's decisionmaking. An information theoretic framework is used to model the decision aids. Thus, it becomes possible to evaluate quantitatively the effect a decision aid has on the workload of a decisionmaker and to derive necessary conditions that preprocessors (a generic form of decision aids) must satisfy in order that they reduce the human's workload.					
20. DISTRIBUTION/AVAILABILITY OF ABSTRACT UNCLASSIFIED/UNLIMITED <input checked="" type="checkbox"/> SAME AS RPT. <input type="checkbox"/> DTIC USERS <input type="checkbox"/>			21. ABSTRACT SECURITY CLASSIFICATION UNCLASSIFIED <b>A</b>		
22a. NAME OF RESPONSIBLE INDIVIDUAL Dr. Marc Q. Jacobs			22b. TELEPHONE NUMBER (Include Area Code) (202) 767-4940		22c. OFFICE SYMBOL NM

DTIC FILE COPY

DTIC  
SELECTE

OCT 15 1985

FEBRUARY 1985

LIDS-P-1438

ANALYSIS OF PREPROCESSORS AND DECISION AIDS IN ORGANIZATIONS\*

by

Gloria H.-L. Chyen

Alexander H. Lewis

Laboratory for Information and Decision Systems

Massachusetts Institute of Technology, Cambridge, MA 02139 USA

COPY

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

16

17

18

19

20

21

22

23

24

25

26

27

28

29

30

31

32

33

34

35

36

37

38

39

40

41

42

43

44

45

46

47

48

49

50

51

52

53

54

55

56

57

58

59

60

61

62

63

64

65

66

67

68

69

70

71

72

73

74

75

76

77

78

79

80

81

82

83

84

85

86

87

88

89

90

91

92

93

94

95

96

97

98

99

100

101

102

103

104

105

106

107

108

109

110

111

112

113

114

115

116

117

118

119

120

121

122

123

124

125

126

127

128

129

130

131

132

133

134

135

136

137

138

139

140

141

142

143

144

145

146

147

148

149

150

151

152

153

154

155

156

157

158

159

160

161

162

163

164

165

166

167

168

169

170

171

172

173

174

175

176

177

178

179

180

181

182

183

184

185

186

187

188

189

190

191

192

193

194

195

196

197

198

199

200

201

202

203

204

205

206

207

208

209

210

211

212

213

214

215

216

217

218

219

220

221

222

223

224

225

226

227

228

229

230

231

232

233

234

235

236

237

238

239

240

241

242

243

244

245

246

247

248

249

250

251

252

253

254

255

256

257

258

259

260

261

262

263

264

265

266

267

268

269

270

271

272

273

274

275

276

277

278

279

280

281

282

283

284

285

286

287

288

289

290

291

292

293

294

295

296

297

298

299

300

301

302

303

304

305

306

307

308

309

310

311

312

313

314

315

316

317

318

319

320

321

322

323

324

325

326

327

328

329

330

331

332

333

334

335

336

337

338

339

340

341

342

343

344

345

346

347

348

349

350

351

352

353

354

355

356

357

358

359

360

361

362

363

364

365

366

367

368

369

370

371

372

373

374

375

376

377

378

379

380

381

382

383

384

385

386

387

388

389

390

391

392

393

394

395

396

397

398

399

400

401

402

403

404

405

406

407

408

409

410

411

412

413

414

415

416

417

418

419

420

421

422

423

424

425

426

427

428

429

430

431

432

433

434

435

436

437

438

439

440

441

442

443

444

445

446

447

448

449

450

451

452

453

454

455

456

457

458

459

460

461

462

463

464

465

466

467

468

469

470

471

472

473

474

475

476

477

478

479

480

481

482

483

484

485

486

487

488

489

490

491

492

493

494

495

496

497

498

499

500

501

502

503

504

505

506

507

508

509

510

511

512

513

514

515

516

517

518

519

520

521

522

523

524

525

526

527

528

529

530

531

532

533

534

535

536

537

538

539

540

541

542

543

544

545

546

547

548

549

550

551

552

553

554

555

556

557

558

559

560

561

562

563

564

565

566

567

568

569

570

571

572

573

574

575

576

577

578

579

580

581

582

583

584

585

586

587

588

589

590

591

592

593

594

595

596

597

598

599

600

601

602

603

604

605

606

607

608

609

610

611

612

613

614

615

616

617

618

619

620

621

622

623

624

625

626

627

628

629

630

631

632

633

634

635

636

637

638

639

640

641

642

643

644

645

646

647

648

649

650

651

652

653

654

655

656

657

658

659

660

661

662

663

664

665

666

667

668

669

670

671

672

673

674

675

676

677

678

679

680

681

682

683

684

685

686

687

688

689

690

691

692

693

694

695

696

697

698

699

700

701

702

703

704

705

706

707

708

709

710

711

712

713

714

715

716

717

718

719

720

721

722

723

724

725

726

727

728

729

730

731

732

733

734

735

736

737

738

739

740

741

742

743

744

745

746

747

748

749

750

751

752

753

754

755

756

757

758

759

760

761

762

763

764

765

766

767

768

769

770

771

772

773

774

775

776

777

778

779

780

781

782

783

784

785

786

787

788

789

790

791

792

793

794

795

796

797

798

799

800

801

802

803

804

805

806

807

808

809

810

811

812

813

814

815

816

817

818

819

820

821

822

823

824

825

826

827

828

829

830

831

832

833

834

835

836

837

838

839

840

841

842

843

844

845

846

847

848

849

850

851

852

853

854

855

856

857

858

859

860

861

862

863

864

865

866

867

868

869

870

871

872

873

874

875

876

877

878

879

880

881

882

883

884

885

886

887

888

889

890

891

892

893

894

895

896

897

898

899

900

901

902

903

904

905

906

907

908

909

910

911

912

913

914

915

916

917

918

919

920

921

922

923

924

925

926

927

928

929

930

931

932

933

934

935

936

937

938

939

940

941

942

943

944

945

946

947

948

949

950

951

952

953

954

955

956

957

958

959

960

961

962

963

964

965

966

967

968

969

970

971

972

973

974

975

976

977

978

979

980

981

982

983

984

985

986

987

988

989

990

991

992

993

994

995

996

997

998

999

1000

ABSTRACT

The use of preprocessors and decision aids in command, control and communication (C<sup>3</sup>) systems is meant to reduce the workload of individual decisionmakers and improve the quality of an organization's decisionmaking. An information theoretic framework is used to model the decision aids. Thus, it becomes possible to evaluate quantitatively the effect a decision aid has on the workload of a decisionmaker and to derive necessary conditions that preprocessors (a generic form of decision aids) must satisfy in order that they reduce the human's workload.

\*This work was supported by the U. S. Air Force Office of Scientific Research under Contract AFOSR-80-0229.

Approved for public release;  
distribution unlimited.

85 10 11 090

# ANALYSIS OF PREPROCESSORS AND DECISION AIDS IN ORGANIZATIONS\*

Gloria H.-L. Chyen  
Alexander H. Lewis  
Laboratory for Information and Decision Systems  
Massachusetts Institute of Technology, Cambridge, MA 02139 USA

**Abstract:** The use of preprocessors and decision aids in command, control and communication (C<sup>3</sup>) systems is meant to reduce the workload of individual decisionmakers and improve the quality of an organization's decisionmaking. An information theoretic framework is used to model the decision aids. Thus, it becomes possible to evaluate quantitatively the effect a decision aid has on the workload of a decisionmaker and to derive necessary conditions that preprocessors (a generic form of decision aids) must satisfy in order that they reduce the human's workload.

**Keywords:** Decision Aids, Organization Theory

## INTRODUCTION

The objective of the research presented in this paper is twofold: (a) to extend a mathematical theory of organizations to include decision aids and (b) to provide an interpretation of some recent experimental results on multiple tasking of decisionmakers. The unifying concept is that of a preprocessor - a processor located between the data source (or stimulus) and the situation assessment stage of a decisionmaker. A simple decision aid can be modeled by an external preprocessor while for interpreting the experimental results an internal preprocessor is introduced.

One function of decision aids is to reduce a decisionmaker's workload. One way of doing that is by pre-processing the incoming data. Another mechanism is to reduce the input rate by filtering out irrelevant data. This saves processing resources and increases the time available to process individual inputs. The decisionmaker need attend only to the significant data and therefore, the system performance is enhanced.

The model of the human decisionmaker used in this paper is the descriptive one presented in Boettcher and Lewis (1982, 1984) and Lewis and Boettcher (1983). The model of the preprocessor is linked to the decisionmaker model so that its ability to reduce the processing workload of the decisionmaker can be analyzed.

The basic information theoretic model of the decisionmaker is a two-stage process with limited processing capacity; it is illustrated in Fig. 1. The decisionmaker receives an input symbol  $x$  from his environment. If the input symbols are generated every  $\tau$  seconds on the average, then  $\tau$ , the mean symbol interarrival time, is a description of the tempo of operations. The situation assessment (SA) stage consists of a finite number of well-defined deterministic or stochastic algorithms that the decisionmaker can choose from to process the measurement  $x$  and obtain the assessed situation  $z$ . The internal decision  $u$  in this stage is the choice of algorithm  $f_i$  to process  $x$ . Therefore, each algorithm is considered to be

active or inactive, depending on the internal decision strategy  $p(u)$ . In the response selection (RS) stage, which is similar to the situation assessment stage, one of the algorithms  $h_j$  is chosen according to the response selection strategy  $p(v|z)$  to process the situation assessment  $z$  into an appropriate response  $y$ . Since no learning takes place during the performance of a sequence of tasks, the successive values taken by the variables of the model are uncorrelated, i.e., the model is memoryless. Hence, all information theoretic expressions in this paper are on a per symbol basis.




Figure 1. Basic Model of Decisionmaking Process

The model of the decisionmaking process shown in Fig. 1 may be viewed as a system  $S$  consisting of two subsystems,  $S^A$  and  $S^R$ , that correspond to each one of the two stages. The input to this system  $S$  is  $x$  and the output is  $y$ . Furthermore, let each algorithm  $f_i$  contain  $a_i$  variables denoted by

$$W^i = \{w_1^i, w_2^i, \dots, w_{a_i}^i\} \quad i = 1, 2, \dots, U \quad (1)$$

and let each algorithm  $h_j$  contain  $a_j'$  variables denoted by

$$W^{U+j} = \{w_1^{U+j}, w_2^{U+j}, \dots, w_{a_j'}^{U+j}\} \quad j = 1, 2, \dots, V \quad (2)$$

It is assumed that the algorithms have no variables in common:

$$W^i \cap W^j = \emptyset \quad \text{for } i \neq j, \quad i, j = 1, 2, \dots, U+V \quad (3)$$

The subsystem  $S^A$  is described by a set of variables

Approved for public release;  
distribution unlimited.

\*This work was supported by the U.S. Air Force Office of Scientific Research under Contract AFOSR-80-0229.

$$S^{SA} = (u, W^1, \dots, W^U, z) \quad (4)$$

and subsystem  $S^{RS}$  by

$$S^{RS} = (v, W^{U+1}, \dots, W^{U+V}, y) \quad (5)$$

The four quantities stated in the Partition Law of Information (Cossant, 1976) for this system  $S$  can be evaluated with the following results.

#### Throughput:

$$G_t = T(x:y) = H(y) - H_x(y) \quad (6)$$

#### Blockage:

$$G_b = T_y(x:u, W^1, \dots, W^{U+V}, z, v) = H(x) - G_t \quad (7)$$

In this case, inputs not received or rejected by the system are not taken into account.

#### Noise:

$$G_n = H_x(S^{SA}, S^{RS}) = H(u) + H(v) \quad (8)$$

#### Coordination:

$$G_c = T(u:W_1^1, \dots, W_{U+V}^{U+V}, z:v:y) = G_c^{SA} + G_c^{RS} + T(S^{SA}:S^{RS}) \quad (9)$$

where

$$G_c^{SA} = \sum_{i=1}^U [p_i g_0^1(p(x)) + a_i H(p_i)] + H(z) \quad (10)$$

$$G_c^{RS} = \sum_{j=1}^V [p_j g_0^{U+1}(p(z|v=j)) + a_j' H(p_j)] + H(y) \quad (11)$$

$$T(S^{SA}:S^{RS}) = H(z) \quad (12)$$

The quantity  $H(x)$  denotes the entropy of the random variable  $x$  and  $H_x(y)$  is the conditional entropy of  $y$  when  $x$  is given. The expression for  $G_n$  shows that it depends on both internal strategies  $p(u)$  and  $p(v|z)$ . In the subsystem coordination expressions  $G_c^{SA}$  and  $G_c^{RS}$ ,  $p_i$  and  $p_j$  are, respectively the probabilities that algorithms  $f_i$  and  $h_j$  have been selected, i.e.,  $p_i = p(u=i)$  and  $p_j = p(v=j)$ . The quantities  $g_0^k$  represent the internal coordination of the corresponding algorithms and depend on the probability distributions of their respective inputs. The quantity  $H$  is the entropy of a Bernoulli random variable with parameter  $p$ :

$$H(p) = -p \log p - (1-p) \log (1-p) \quad (13)$$

Eq. (9) states that the total coordination in the system  $S$  can be expressed as the sum of the internal coordination within each subsystem given by Eqs. (10) and (11) and the coordination due to the interaction between the two subsystems given by Eq. (12).

The subsystem coordination consists of terms reflecting the presence of switching due to the

internal decision strategies  $p(u)$  or  $p(v|z)$ . If there is no switching, i.e., if, for example  $p(u=i)=1$  for some  $i$ , then  $H$  will be identically zero and Eq. (10) will reduce to:

$$G_c^{SA} = g_0^1(p(x)) + H(z) \quad (14)$$

Finally, the total information processing activity of the system  $G$  is given by

$$G = G_t + G_b + G_n + G_c; \quad (15)$$

it can serve as a measure of the workload of the decisionmaker is carrying out this task. (Boettcher and Levis, 1982)

The paper has been organized as follows. In the next section, the basic model of preprocessors and decision aids is introduced. The preprocessor model is connected to the decisionmaker model for system evaluation. A numerical example is provided to illustrate the utility of a preprocessor in a decisionmaking system. Also, guidelines for the role of preprocessors in decisionmaking systems are developed. In the final section the question of how a preprocessor can facilitate dual-task processing by a decisionmaker is investigated by formulating two versions of a dual-task problem, and analyzing one of them.

#### THE PREPROCESSOR MODEL

A preprocessor (PP) is located between a source and a decisionmaker (DM). In the simplest case considered here the PP operates on the decisionmaker's input variable only; hence, the PP consists of a single algorithm for preliminary processing of the input. It yields a SA decision strategy,  $p(u|x)$ , and sometimes a modified input  $z$  to the DM. Consequently, if the function of a PP is specified, i.e., the algorithm and the interconnections of the internal variables, the activity within the PP is computable, just like for the other algorithms within the SA and RS stages of the DM model.

A simple example of a PP illustrates how the various activity terms can be computed for a specified algorithm with well-defined internal variables. The function of the preprocessor in this example is to reduce the workload of the decisionmaker by processing some of the data before they are received by the DM. In order to evaluate the utility of the PP, two different decisionmaking systems, shown in Figs. 2 and 3, are considered.

The first one represents an unaided DM while the second one represents a DM with a preprocessor. The DMs in both systems is identical structures and algorithms. The PP in the second system is an algorithm that performs the same function as the SA stage of the first DM system. Since the PP is just an algorithm without any decisionmaking capability, the SA stage of the first DM system has to employ a pure strategy, i.e., the same algorithm is always selected to process the arriving inputs. Under such conditions, the decisionmaking process in both systems are identical. In order to allow the two systems to do the same task with the same performance, so that the activity or workload can be compared properly, the algorithms within the processes are assumed to be deterministic and their output distributions  $p(y)$  identical. The latter result will be ensured, if the RS stage in the DM of both systems has the same input distribution  $p(z)$  and decision strategy  $p(v|z)$ . Since the second system has executed the SA job within its preprocessor, its SA stage simply transmits its input to an identity algorithm so that the

distribution  $p(z)$  within both systems will be identical.




Figure 2. Basic DM System

With such a processing setup, the two systems carry out the same task with the same performance. To demonstrate the utility of the PP in the second system, the total activity within each system has to be evaluated.




Figure 3. Aided DM System

Let:

$$G_{DM_1} = \text{Activity within First System} \quad (16a)$$

$$G_{DM_2} + G_{PP} = \text{Activity within Second System} \quad (16b)$$

where  $G_1$  is the total activity with subsystem 1.

The expression for the total activity of a decisionmaker is given by:

$$G_{DM} = H(x) + H(u) + \sum_{i=1}^U p_i \epsilon_0^i + \sum_{i=1}^U a_i H(p_i) + H(z) + H_2(v) + \sum_{j=1}^V p_j \epsilon_0^{U+j} (p(z|v=j)) + \sum_{j=1}^V a'_j H(p_j) + H(y) + H(z) \quad (17)$$

Since the response selection process, input distribution  $p(z)$  and decision strategy  $p(v|z)$  of the RS stage in both systems are assumed identical, the activity within the RS stage of the two systems is the same, denoted by  $G_{RS}$ .

$$G_{RS} = H_2(v) + \sum_{j=1}^V p_j \epsilon_0^{U+j} (p(z|v=j)) + \sum_{j=1}^V a'_j H(p_j) + H(y) + H(z) \quad (18)$$

Assume that the pure strategy in the SA stage of

the first system is such that the  $i^{\text{th}}$  algorithm is always selected (i.e.,  $p(u=i)=1$ ) whereas in the second system the first algorithm, which is an identity algorithm, is always selected. Then the activity of each decisionmaker in the two systems is obtained from the expressions in Eqs. (17) and (18)

$$G_{DM_1} = H(x) + \epsilon_0^1 + H(z) + G_{RS} \quad (19a)$$

$$G_{DM_2} = H(x') + \epsilon_0^1 + H(z) + G_{RS} \quad (19b)$$

The preprocessor in the second system consists of a single algorithm without any decisionmaking capability. The algorithm in this case is identical to the  $i^{\text{th}}$  algorithm of the SA stage, hence the activity within the PP is simply

$$G_{PP} = H(x) + \epsilon_0^1 \quad (20)$$

The function of the identity algorithm  $f_1(\cdot)$  is to transmit its input to its output without any internal processing. Therefore, there is only one output variable  $z$  which duplicates the input value  $x$  and there are no internal variables. Its internal coordination is then

$$\epsilon_0^1 = T(\phi; z) = 0 \quad (21)$$

Since the internal coordination of any nontrivial algorithm (i.e., other than the identity algorithm) is greater than zero,  $\epsilon_0^1 > 0$ , it follows that

$$\epsilon_0^1 > \epsilon_0^2 \quad (22)$$

Given that the PP contains a deterministic algorithm without any decisionmaking capability, then

$$H(x) \geq H(x') > 0. \quad (23)$$

According to Eqs. (19a) to (23), the following two inequalities will always be valid.

$$G_{DM_1} > G_{DM_2} \quad (24)$$

$$G_{DM_1} < G_{DM_2} + G_{PP} \quad (25)$$

From the expressions of the total activity within the two DM systems given in Eqs. (15) and (16), the inequalities in Eqs. (24) and (25) show that even though the workload of the first system is less than that of the second system, the presence of the PP makes the workload of the second decisionmaker to be less than that of the first one. This result establishes a preprocessor's ability to reduce the activity of a decisionmaker. Therefore, decision aids that perform part of the situation assessment, e.g., some of the signal processing, are indeed useful devices, because they reduce some of the decisionmaker's processing load.

#### THE DUAL-TASK PROBLEM

Another application of the preprocessor is to facilitate a decisionmaker in handling two

concurrent tasks. When the measure of performance is properly defined the system performance of the dual-task case can be compared with that of single-task case.

Two variants of the dual-task problem have been investigated (Chyen, 1984). One is the sequential dual-task problem in which inputs of two different tasks arrive one after another in a sequential manner. The other is the parallel dual-task problem in which inputs of the two tasks arrive in parallel in a synchronous manner. For the single-task case, the input arrival rate will be identical to the rate of the dual-task case in order to compare properly the two workloads.

In this section, the sequential dual-task problem in the context of a single decisionmaker aided by a preprocessor will be formulated and then analyzed to determine the effect that executing two non-synergistic tasks can have on system performance.

The model of the sequential dual-task processing shown in Fig. 4 consists of a preprocessor and a decisionmaker.




Figure 4. Sequential Dual-Task Processing Model

The input  $x$  of the system may be from task A with input alphabet  $X_A$ , or task B with input alphabet  $X_B$ . The PP examines each individual input to distinguish the task to which the particular input belongs. If it is a task A input, then the PP will yield a decision strategy  $p(u_A)$  pertaining to task A to the DM for processing the input; otherwise strategy  $p(u_B)$  pertaining to task B will be generated.

These decision strategies are the variables determining system activity and system performance. A pure or deterministic strategy means that a specific algorithm is always chosen to process the inputs from that particular task. A mixed or stochastic strategy is one obtained as a convex combination of pure strategies. In order to simplify the analysis that follows, it is assumed that there are only two pure strategies available for each individual task. When the four pure strategies of the two tasks are denoted by  $u_A^1, u_A^2, u_B^1, u_B^2$ , the mixed strategies  $u_A$  and  $u_B$  of the two tasks can be written as functions of decision strategy parameters  $\delta_A$  or  $\delta_B$  which correspond to the probabilities of employing pure strategies  $u_A^1$  and  $u_B^1$  respectively.

$$u_j = \delta_j u_j^1 + (1-\delta_j) u_j^2 \quad 0 \leq \delta_j \leq 1 \quad j=A,B \quad (26)$$

Again, for the sake of simplicity, only the decision strategies of the 3A stage are considered. The situation assessment variable  $z$  is the system output.

Given that  $z'$  is the desired decision response, the performance  $J$  of a decisionmaking task can be defined as the probability of error in determining  $z$ . Since two tasks are being performed, their measures of performance  $J_A$  and  $J_B$  are defined as the probabilities of error in executing task A and task B respectively.

$$J_j = p(x \neq z') | x \in X_j \quad j = A,B \quad (27)$$

If the performance measure, evaluated when a pure strategy is in effect, is denoted by  $J_A^1$  and  $J_B^1$ , respectively, then the quantities  $J_A$  and  $J_B$  can be rewritten as functions of the parameters  $\delta_A$  and  $\delta_B$  that specify the decision strategies  $u_A$  and  $u_B$ :

$$J_j(\delta_j) = \delta_j J_j^1 + (1-\delta_j) J_j^2 \quad j = A,B \quad (28)$$

Now the measure of overall performance for the system can be defined by the probability of making a task A error or a task B error. If  $\alpha$  is the probability of the system processing task A inputs, then by assuming errors on both tasks to be equally detrimental the system performance  $J$  can be written as

$$J(\alpha) = \alpha J_A(\delta_A) + (1-\alpha) J_B(\delta_B) \quad 0 \leq \alpha \leq 1 \quad (29)$$

Graphically, for a fixed  $\alpha$ , the system performance  $J$  can be plotted as a tilted plane with boundaries at the planes  $\delta_A=0$  and 1 and  $\delta_B=0$  and 1. The plane in the 3-dimensional space  $(J, \delta_A, \delta_B)$  is shown in Fig. 5.




Figure 5. Total Performance Versus Decision Strategy Parameters  $\delta_A$  and  $\delta_B$

The total activity of the system for single-task processing is a convex function of the decision strategy parameters  $\delta_A$  and  $\delta_B$ , whereas that of dual-task processing is a convex function of the task division parameter  $\alpha$  as well as the decision strategy parameters  $\delta_A$  and  $\delta_B$ . The convexity of the system activity  $G$  in  $\alpha$  as well as in  $\delta_A$  and  $\delta_B$  has been demonstrated by Hall (1982).

$$G_j(\delta_j) \geq \delta_j G_j^1 + (1-\delta_j) G_j^2 \quad j = A,B \quad (30)$$

$$G(\alpha) \geq \alpha G_A(\delta_A) + (1-\alpha) G_B(\delta_B) \quad (31)$$

A typical graph of  $G$  for a fixed  $\alpha$  is shown in Fig. 6.

The system activity or workload in Fig. 6 is a curved bounded surface with four corners (somewhat like a tent). When, for a fixed  $\alpha$ ,  $J$  is plotted against  $G$ , parametrically with respect to  $(\delta_A, \delta_B)$  the performance-workload locus for the whole system can be constructed.






Figure 6. Total Workload Versus Decision Strategy Parameters  $\delta_A$  and  $\delta_B$

To simplify the construction of the locus, but without any loss of generality, it is assumed that  $\delta_A = \delta_B = \delta$ , i.e., both task A and task B employ the same rule in decisionmaking (but the content of the decisions may be different). For example, if there are four algorithms  $f_1, f_2, f_3$ , and  $f_4$  in the DM, the pure strategies of the two tasks can be defined as employing different algorithms. For instance, for task A:  $u_A^1$  means  $u=1$ ;  $u_A^2$  means  $u=2$ ; while for task B:  $u_B^3$  means  $u=3$  and  $u_B^4$  means  $u=4$ . Then the mixed strategies,  $u_A$  and  $u_B$ , will have the same form but different content in the decisionmaking process.

$$u_j = \delta u_j^1 + (1-\delta)u_j^2 \quad j = A, B \quad (32)$$

With such a formulation, Fig. 6 will degenerate into the 2-dimensional plot shown in Fig. 7.




Figure 7. Workload Versus Decision Strategy Parameter  $\delta$

Therefore, the J-G plot of the system for a fixed  $\epsilon$  can be drawn parametrically with respect to  $\delta$  (Fig. 8).




Figure 8. System Workload Performance Locus

If for all the different relative task frequencies, i.e.,  $0 \leq \epsilon \leq 1$ , the assumption

$\delta_A = \delta_B = \delta$  is always kept, then J-G plots similar to that in Fig. 8 can be drawn for each value of  $\epsilon$ . To display all these J-G plots in such a format that the performance of single-task processing and dual-task processing can be compared, G can be plotted in a polar coordinate plane with its radial coordinate being the system performance J and the angular coordinate being proportional to the task division parameter  $\epsilon$ , i.e.,

$$\theta \in [0, \frac{\pi}{2}] \quad \epsilon \in [0, 1]$$

where  $\epsilon = (\theta/\pi/2)$ .

Therefore, a typical J-G plot of the system for all possible values of  $\epsilon$  may look like the curved surface in Fig. 9 which resembles part of the surface area of a toroid with curved edges. Its edges at  $\delta=0$  and  $\delta=1$  are curved upward with respect to G because, for a particular decision strategy, the system activity G is a convex function of the task division parameter  $\epsilon$ . The other two edges of the curved surface in Fig. 9 are the J-G plots for the single task processing. The projection of the surface on the J- $\epsilon$  plane will be a curved area in the shape of a quarter toroid as shown in Fig. 10.




Figure 9. System Workload Performance Locus of Changing Task Division Parameter  $\epsilon$ .

When the system exhibits bounded rationality behavior, the plane of the activity threshold G may cut through the curved surface in Fig. 9. The surface above the cut corresponds to the region where the workload exceeds the bounded rationality constraint. The remaining surface represents the region with admissible strategies. The projection of the remaining surface on the J- $\epsilon$  plane will allow comparison of performance between single-task processing and dual-task processing. Depending on the numerical specifications of the problem, the projection of the region that results from admissible strategies may look like Fig. 11.




Figure 10. Projection of Fig. 9 on the J- $\epsilon$  Plane




Figure 11. Projection of Locus Due to Admissible Strategies on the  $J$ - $a$  plane.

The locus in Fig. 11 is obtained by considering a plane of constant  $G$  in Fig. 9 that is above the  $\delta=1$  boundary of the  $(G, J_A, J_B)$  surface and intersects the  $\delta=0$  boundary. This is illustrated in Fig. 12. For  $\delta=0.3$ , a large central segment of the  $G$ - $a$  curve exceeds the threshold level  $G_p$ . Because of the convexity of the  $G$ - $a$  curves, the eliminated segment is defined by the interval  $(a_1, a_2)$ . Similarly, a segment of the  $\delta=0$  curve, the  $\delta=0.6$  curve, and the ones for intermediate values of  $\delta$ , are eliminated. This results in the shape shown in Fig. 11.




Figure 12.  $G$ - $a$  curves for various values of  $\delta$

It can be observed in Fig. 11 that under the constraint of bounded rationality ( $G \leq G_p$ ), the decisionmaker doing a single, or almost a single task, achieves a wider range of performance values, including the optimum ones. This is evidenced by the locus near the axes  $a=0$  and  $a=1$ . When both tasks have to be carried out, the range of values of the performance is smaller; many of the better values are not achievable. Such a deficiency can be explained by the need for extra time and energy for a decisionmaker to adjust in handling a different task. Hence, in general, a decisionmaker performs better in processing a single task than processing two different tasks in sequence, even though the incoming task rate for both cases are the same. These results, based on the analytical model, are consistent with the experimental results obtained by Kelly and Greitzer (1982) and provide a plausible interpretation for the observed degradation of performance.

#### CONCLUSIONS

One of the uses of a preprocessor is to reduce the workload in the situation assessment stage of a decisionmaker by processing the input data.

A preprocessor can also be used to facilitate a decisionmaker in handling a dual-task. Such a preprocessor functions as a matching algorithm to yield appropriate decision strategies for processing two kinds of inputs. It has been shown that a decisionmaker carrying out a dual-task cannot perform any better than when he executes a single task. This is due to the readjustment effort required by the decisionmaker to handle the different, non-synergistic tasks. The analytical results provide an interpretation of recent experimental results.

The main focus of this paper was to present models of preprocessors and methods for their analysis. This constitutes the first step in the development of a mathematical theory and procedures for the design of decision aids. Indeed, several simple necessary conditions have been derived that decision aids must satisfy, if their effect is not to be detrimental to the decisionmaker, i.e., if they are not to cause degradation of a decisionmaker's performance.

#### REFERENCES

- Boettcher, K. L. and A. H. Lewis (1982). Modeling the Interacting Decisionmaker with Bounded Rationality. IEEE Trans. on Systems, Man, and Cybernetics, Vol. SMC-13, No. 3.
- Boettcher, K. L. and Lewis (1983). Modeling and Analysis of Teams of Interacting Decisionmakers with Bounded Rationality. Automation, Vol. 9, No. 6.
- Chyen, H.-L. (1984). Information Theoretic Models of Preprocessors and Decision Aids. MS Thesis, LIDS-TN-1377, Laboratory for Information and Decision Systems, MIT.
- Connat, R. C. (1976). Laws of Information Which Govern Systems. IEEE Trans. on Systems, Man, and Cybernetics, Vol. SMC-6, No. 4.
- Hall, S. A. (1982). Information Theoretic Models of Storage and Memory. SM Thesis, LIDS-TN-1232, Laboratory for Information and Decision Systems, MIT, Cambridge, MA.
- Kelley, R. T., and F. L. Greitzer (1982). Effects of Task Load on Decision Performance in Simulated Command and Control Operations. SPEDC-TN-82-21, Navy Personnel Research and Development Center, San Diego, CA.
- Lewis, A. H., and K. L. Boettcher (1983). Decisionmaking Organizations with Acyclical Information Structures. IEEE Trans. on Systems, Man, and Cybernetics, Vol. SMC-13, No. 3.

**END**

**FILMED**

**11-85**

**DTIC**